

Rec'd PCT/PTO 21 DEC 2004

PCT/EP 03/06295



Europäisches
Patentamt

European
Patent Office

Office européen
des brevets

#2

10/519306

REC'D 19 SEP 2003

WIPO

PCT

Bescheinigung

Certificate

Attestation

Die angehefteten Unterla-
gen stimmen mit der
ursprünglich eingereichten
Fassung der auf dem näch-
sten Blatt bezeichneten
europäischen Patentanmel-
dung überein.

The attached documents
are exact copies of the
European patent application
described on the following
page, as originally filed.

Les documents fixés à
cette attestation sont
conformes à la version
initialement déposée de
la demande de brevet
européen spécifiée à la
page suivante.

Patentanmeldung Nr. Patent application No. Demande de brevet n°

02291605.0

Der Präsident des Europäischen Patentamts;
Im Auftrag

For the President of the European Patent Office

Le Président de l'Office européen des brevets
p.o.

**READY FOR
PUBLICATION**
21 AUGUST 2003

R C van Dijk



Anmeldung Nr:
Application no.: 02291605.0
Demande no:

Anmeldetag:
Date of filing: 28.06.02
Date de dépôt:

Anmelder/Applicant(s)/Demandeur(s):

MOTOROLA, INC.
1303 East Algonquin Road
Schaumburg, IL 60196
ETATS-UNIS D'AMERIQUE

Bezeichnung der Erfindung/Title of the invention/Titre de l'invention:
(Falls die Bezeichnung der Erfindung nicht angegeben ist, siehe Beschreibung.
If no title is shown please refer to the description.
Si aucun titre n'est indiqué se référer à la description.)

Low drop-out voltage regulator and method

In Anspruch genommene Priorität(en) / Priority(ies) claimed /Priorité(s)
revendiquée(s)
Staat/Tag/Aktenzeichen/State/Date/File no./Pays/Date/Numéro de dépôt:

Internationale Patentklassifikation/International Patent Classification/
Classification internationale des brevets:

H02M/

Am Anmeldetag benannte Vertragsstaaten/Contracting states designated at date of
filing/Etats contractants désignées lors du dépôt:

AT BE CH CY DE DK ES FI FR GB GR IE IT LI LU MC NL PT SE TR

LOW DROP-OUT VOLTAGE REGULATOR AND METHOD

Field of the Invention

5

This invention relates to voltage regulators, and particularly to low drop-out (LDO) voltage regulators.

10 **Background of the Invention**

A low drop-out voltage regulator is a regulator circuit that provides a well-specified and stable DC voltage (whose input-to-output voltage difference is typically
15 low). The operation of the circuit is based on feeding back an amplified error signal which is used to control output current flow of a pass device (such as a power transistor) driving a load. The drop-out voltage is the value of the input/output differential voltage where
20 regulation is lost.

The low drop-out nature of the regulator makes it appropriate (over other types of regulators such as dc-dc converters and switching regulators) for use in many
25 applications such as automotive, portable, and industrial applications. In the automotive industry, the low drop-out voltage is necessary during cold-crank conditions where an automobile's battery voltage can be below 6V. Increasing demand for LDO voltage regulators is also
30 apparent in mobile battery operated products (such as cellular phones, pagers, camera recorders and laptop computers), where the LDO voltage regulator typically

needs to regulate under low voltage conditions with a
reduced voltage drop.

A typical, known LDO voltage regulator uses a
5 differential transistor pair, an intermediate stage
transistor, and a pass device coupled to a large
(external) bypass capacitor. These elements constitute a
DC regulation loop which provides voltage regulation.

10 For the (LDO) low drop-out voltage, generally in the
closest known technology the load capacitor forms the
dominant pole, and due to this the capacitor has to be
specified with a minimum and maximum serial resistance.
As the load is part of the regulation loop, it is
15 possible for instability to be caused by such
indeterminate factors as parasitic capacitance.

However, this approach has the disadvantage(s) that,
since the load is part of the regulation loop:

- 20 • the LDO regulator typically needs an external
capacitor in order to ensure stability.
- the loop DC gain changes versus the load resistance
and the capacitor value
- the capacitor has to be specified with a minimum and
25 maximum ESR (Equivalent Serial resistor)

A need therefore exists for a low drop-out voltage
regulator in wherein the abovementioned disadvantage(s)
may be alleviated.

30

Statement of Invention

In accordance with the present invention there is provided a low drop-out voltage regulator and a method
5 for low drop-out voltage regulation as claimed in claim 1 and claim 11 respectively.

Brief Description of the Drawings

10

One low drop-out voltage regulator, in which the load capacitor is not used "for dominant pole", incorporating the present invention will now be described, by way of example only, with reference to the accompanying
15 drawings, in which:

FIG. 1 shows a schematic circuit diagram of a conventional LDO voltage regulator in which the output is high impedance and the load (and hence the load capacitor) are part of the voltage regulation
20 loop;

FIG. 2 is a graph illustrating pole tracking behaviour of the circuit of FIG. 1;

25

FIG. 3 shows a schematic circuit diagram of an LDO voltage regulator incorporating the present invention;

30 FIG. 4 is a graph illustrating operational behaviour of a main loop of the circuit FIG. 3;

FIG. 5 is a graph illustrating operational behaviour
of an impedance follower arrangement of the circuit
portion of FIG. 3;

5 FIG. 6 shows a block-schematic representation of the
LDO voltage regulator of FIG. 3;

FIG. 7 is a graph illustrating operational behaviour
of the circuit of FIG. 3.

10

Description of Preferred Embodiment

Referring firstly to FIG. 1, a prior-art, conventional
15 LDO voltage regulator (100) uses a differential
transistor pair arrangement (T1-T4), an intermediate
stage transistor arrangement (T5-T6), and a pass device
(T7) coupled to a large (external) bypass capacitor (CL)
having an equivalent series resistance (ESR). The
20 differential transistor pair arrangement (T1-T4) receives
a BandGap reference voltage (V_{bg}), and is supplied with a
supply voltage (V_{Supply}) through a voltage source (VS).
These elements constitute a DC regulation loop which
provides low drop-out voltage regulation of an Output
25 Voltage applied to the external bypass/load capacitor
(CL).

The bypass/output PMOS device (T7) allows a low drop-out
voltage to be obtained between Supply and Output voltage,
30 but as the output is made with the drain of the PMOS
device (T7), the output is high impedance and the load
(and hence the load capacitor) are part of the loop.

Since the load capacitor (CL) is used in the main loop of the regulator, the external capacitor (CL) will affect the stability of the loop due purely to its capacitance or too high a value of ESR.

5

Referring now also to FIG. 2, the plot of gain (A) of the voltage regulation loop against frequency (f) shows a dominant pole (Fpout) created by the output capacitor (CL), a zero (Zesr) created by the ESR of the output
10 capacitor (CL), a further sub-dominant pole (Fpdiff) created by the differential pair arrangement (T1-T4) and a further sub-dominant pole (Fpin) created by the intermediate stage (T5-T6). It will be understood that the use in the intermediate stage of device T5 alone
15 produces the plot shown in full line in FIG. 2, and that the use additionally of device T6 allows pole tracking of the poles Fpout and Fpin as shown by the arrowed dashed lines in the figure.

20 Referring now to FIG. 3, an improved LDO voltage regulator 300 has a differential amplifier B, whose inputs are respectively connected via a resistive divider r_1 , r_2 and via a source of reference voltage v_{ref} to an output node. The output of the differential amplifier B
25 is connected to the base of a bipolar PNP transistor Q1, whose emitter is connected to the output node, and whose collector is connected via a source of DC current I_{dc} to a ground rail. A cascoded bipolar NPN transistor Q2 has its emitter connected to the collector of transistor Q1,
30 and has its base connected via a source of bias voltage V_b to the ground rail. The collector of the transistor Q2 is connected via a resistor r_g to a rail of supply

voltage V_{bat} . A PMOS transistor Q3 has its current electrodes connected between the supply rail and the output node, and has its control electrode connected to the collector of transistor Q2. Although the transistor Q3 is shown as an MOS device, it will be understood that a bipolar P-type transistor, i.e., a PNP device could alternatively be used. A capacitor C_g is connected between the output node and the collector of transistor Q2. The output node is connected to a load represented by a load capacitor C_L , a load resistor r_L and a resistor r_s . It will be understood that the transistor Q3 is connected in 'common source' configuration, and has a non-unity open-loop gain which in closed-loop mode becomes a unity gain since the output V_{out} is connected with the emitter of transistor Q1. In use of the LDO voltage regulator 300, an input voltage v_{in} is developed at the output of the differential amplifier B, an input current i_{in} flows into the emitter of the transistor Q1, a current i_x flows across the resistor r_g , and an input current i_{out} flows from the transistor Q3 to the output node. It will be understood that the transistor Q1 has a transconductance gm_1 and the transistor Q3 has a transconductance gm_2 .

The LDO voltage regulator circuit 300 can be considered in two parts:

- a 'main loop' 310 comprising the resistive divider r_1 , r_2 and the differential amplifier B; and
- a 'follower impedance' 320 comprising the remaining components of FIG. 3 (as will be explained in more detail below, the 'follower impedance' provides an

impedance adaptor providing a high input impedance and a low output impedance and a follower amplifier having closed-loop unity gain).

- 5 Referring now also to FIG. 4, the open-loop operational behaviour of the 'main loop' 310, plotted as gain versus pulsation (frequency), shows that with increasing frequency the gain has a maximum value of BK (where B is the gain of the differential amplifier B , and $K = \frac{r_1}{r_2 + r_1}$)
- 10 up to a dominant pole at frequency ω_{pd} , (thereafter decreasing and crossing zero at a frequency ω_{0d}). It can be shown that the ratio of v_{in} and v_{out} , the open-loop gain B_{OL} , is given by:

$$\frac{v_{in}}{v_{out}} = B_{OL} = B.K \frac{1}{1 + j \left(\frac{\omega}{\omega_{pd}} \right)}$$

15

- Referring now also to FIG. 5, the operational behaviour of the 'follower impedance' 320, plotted as open-loop gain A_{OL} versus pulsation (frequency), shows that with increasing frequency the gain begins at a maximum value
- 20 A_{max} , and decreases (starting at a pole at a frequency ω_p , and ending at a pole at a frequency ω_2 , and crosses a zero value at a frequency ω_0). It will be understood that the closed-loop gain A_{CL} (shown in dashed line) of the 'follower impedance' 320 begins at a zero value up to
- 25 the frequency ω_0 , and thereafter becomes the same as the open-loop gain A_{OL} , decreasing to the minimum value A_{min} at the frequency ω_2 . It can be shown that the open-loop gain A_{OL} is given by:

$$A_{OL} = (G_i + 1)gm_1 r_L \left(\frac{1 + j\frac{\omega}{\omega_2}}{1 + j\frac{\omega}{\omega_p}} \right)$$

where $G_i = \frac{i_{out}}{i_{rg}}$, $\omega_p = \frac{1}{(r_L + r_s)c_L}$, $\omega_2 = \frac{1}{r_s c_L}$, $\omega_o = \frac{1}{\frac{r_e}{(G_i + 1)} c_L}$,

$A_{max} = gm_1(G_i + 1)r_L$, and at high frequencies $A_{min} = \frac{r_s}{r_e}(G_i + 1)$,

and that the closed loop gain is given by:

5
$$A_{CL} = \frac{1}{1 + j\left(\frac{r_e c_L \omega}{G_i + 1}\right)}$$

where r_e , the dynamic impedance of the transistor Q1, is equal to $\frac{1}{gm_1}$.

10 It will be noted that the load impedance (r_L) appears in the open loop gain (A_{OL}), but not in the closed-loop gain (A_{CL}) where $V_{out} = V_{in}$. It will be understood that this results in DC output current not changing the closed-loop gain.

15 It will therefore be understood that in the LDO voltage regulator 300 transistor Q1 creates a low output impedance with an emitter follower, and the load capacitance is divided by the current gain of the second stage. Therefore, the pole created by the load
20 capacitance is high, because RC is low (R low due to the emitter follower, C low due to the output capacitor's value being divided by, for example, 1000). The dominant pole is given by the amplifier compensation (main loop

with amplifier B) and not dependant on the load (up to a load of, for example, 10 μ F).

Referring now also to FIG. 6, it will be appreciated that
5 in a block diagrammatic representation the LDO voltage regulator 300 has a main loop 310 which contributes a dominant pole T1, an output loop provided by the 'follower impedance' 320 which contributes sub-dominant pole T2, and internal DC feedback 330. It will be
10 understood that in the gains of the blocks 310 and 320 of FIG. 6, the symbol s represents the Laplace operator.

Referring now also to FIG. 7, the cumulative effect of the poles T1 and T2 can be seen in the overall gain A of
15 the regulation control loop in the LDO voltage regulator 300. As can be seen, the internal pole T1 provided by the amplifier B is a dominant, ultra-low pole. It can also be seen that no dominant pole is created by the output bypass capacitor CL, allowing strong stability for
20 any capacitor used for this function. The pole created by CL (1/T2) appears when the gain is less than 1 and not before. Tests have shown that the LDO voltage regulator 300 exhibits good stability and low variation for a range of values of output capacitance.

25

It will be understood that the low drop-out voltage regulator where the load capacitor is not used "for dominant pole" described above provides the following advantages:

- 30 1. The output capacitor can be dramatically reduced in size, or may be removed (a low dominant pole, provided by the main loop with amplifier B, allows

the LDO voltage regulator 300 to work with a 0nF
output capacitor).

2. Internal power consumption can be reduced (for
example, 100 μ A may be enough to drive the full
output current, up to 100mA current limit),
providing improved regulator efficiency.
3. Low output impedance is produced (the DC output
resistance is very low, less than 10 m Ω , for
example).
4. The external capacitor can have a ESR (equivalent
serial resistor) of zero.

It will be understood that the low voltage drop-out
regulator 300 will typically be fabricated in an
integrated circuit (not shown).

It will be further appreciated that other alternatives to
the embodiment of the invention described above will be
apparent to a person of ordinary skill in the art. For
example, the PMOS transistor Q3 may be cascoded to
increase the output impedance in order to improve line
transient performance of the LDO regulator.

Claims

1. A low drop-out voltage regulator comprising:
transistor means (Q1-Q2) for receiving a
reference voltage and in dependence thereon
5 producing a regulated output voltage;
an output stage (Q3) for coupling to a load;
and
control loop means (310) coupled to the
10 transistor means for providing a dominant pole,
whereby stability of operation may be obtained with
a lower load capacitance.
2. The low drop-out voltage regulator as claimed in
15 claim 1 wherein the control loop means (310) comprises:
differential amplifier means (B) having an
output coupled to the transistor means (Q1, Q2); and
voltage divider means (r_1 , r_2) coupled between
the voltage regulator output and a first input of
20 the differential amplifier means.
3. The low drop-out voltage regulator as claimed in
claim 2 wherein the control loop means (310) further
comprises:
25 voltage reference means coupled between the
voltage regulator output and a first input of the
differential amplifier means.
4. The low drop-out voltage regulator as claimed in
30 claim 1, 2 or 3 wherein the output stage (Q3) comprises a
low impedance output.

5. The low drop-out voltage regulator as claimed in
~~claim 4 wherein the output stage (Q3) comprises a closed-~~
loop amplifier (Q3).

5 6. The low drop-out voltage regulator as claimed in
claim 5 wherein the closed loop amplifier (Q3) comprises
a unity gain amplifier.

7. The low drop-out voltage regulator as claimed in any
10 preceding claim wherein the transistor means (Q1-Q2)
comprises a cascode transistor arrangement.

8. The low drop-out voltage regulator as claimed in any
preceding claim wherein the output stage comprises a
15 cascode transistor arrangement.

9. The low drop-out voltage regulator as claimed in any
preceding claim wherein the output stage comprises a P-
type transistor.

20 10. The low drop-out voltage regulator as claimed in
claim 9 wherein the P-type transistor is a PMOS
transistor.

11. A method for low drop-out voltage regulation comprising:

providing transistor means (Q1-Q2) receiving a reference voltage and in dependence thereon
5 producing a regulated output voltage;
providing an output stage (Q3) for coupled to a load; and
providing control loop means (310) coupled to the transistor means and providing a dominant pole,
10 whereby stability of operation may be obtained with a lower load capacitance.

12. The method for low drop-out voltage regulation as claimed in claim 11 wherein the control loop means (310)

15 comprises:

differential amplifier means (B) having an output coupled to the transistor means (Q1, Q2); and
voltage divider means (r_1 , r_2) coupled between the voltage regulator output and a first input of
20 the differential amplifier means.

13. The method for low drop-out voltage regulation as claimed in claim 12 wherein the control loop means (310) further comprises:

25 voltage reference means coupled between the voltage regulator output and a first input of the differential amplifier means.

14. The method for low drop-out voltage regulation as
30 claimed in claim 11, 12 or 13 wherein the output stage (Q3) comprises a low impedance output.

15. The method for low drop-out voltage regulation as
~~claimed in claim 14 wherein the output stage (Q3)~~
comprises a closed-loop amplifier (Q3).

5 16. The method for low drop-out voltage regulation as
claimed in claim 15 wherein the closed loop amplifier
(Q3) comprises a unity gain amplifier.

17. The method for low drop-out voltage regulation as
10 claimed in any one of claims 11-16 wherein the transistor
means (Q1-Q2) comprises a cascode transistor arrangement.

18. The method for low drop-out voltage regulation as
claimed in any one of claims 11-17 wherein the output
15 stage comprises a cascode transistor arrangement.

19. The method for low drop-out voltage regulation as
claimed in any one of claims 11-18 wherein the output
stage comprises a P-type transistor.

20

20. The method for low drop-out voltage regulation as
claimed in claim 19 wherein the P-type transistor is a
PMOS transistor.

25 21. An integrated circuit comprising the low drop-out
voltage regulator of any one of claims 1-10.

Abstract

LOW DROP-OUT VOLTAGE REGULATOR AND METHOD

5 A low drop-out voltage regulator (300) and method
comprising: a differential transistor arrangement (Q1-Q2)
for receiving a reference voltage and in dependence
thereon producing a regulated output voltage; an output
stage (Q3) for coupling to a load; and a control loop
10 (310) coupled to the differential transistor arrangement
for providing a dominant pole. Since a load capacitance
is not used for dominant pole, stability of operation may
be obtained with a lower load capacitance. The output
stage is preferably a closed-loop unity gain amplifier
15 providing a low impedance output.

This provides the following advantages:

- 1 - The output capacitor can be dramatically reduced or removed (a low dominant pole, allows the regulator to work with 0nF output capacitor).
- 20 2 - internal power consumption can be reduced, improving regulator efficiency.
- 3 - Low output impedance is provided, with very low DC output resistance.
- 4 - The load capacitor can have zero ESR (equivalent
25 serial resistance).

FIG. 1
Prior Art





FIG. 2
Prior Art



300 



FIG. 4




FIG. 5





FIG. 6






FIG. 7